



DA-1AS/DA-1AG

Two-wire Electric Lock
Door Phone Kit



**Provides Entry Security
for your Residence**

Simplified Two-Wire Door Entry Kit

System Configuration



EL-9S
Electric door
release.

DA-1DS
Door station.

DA-1DG
Door station.

DA-1MD
Master station.

DAR-1
Call extension
rounder.

Features

- Connect Electric Door Release with same two wires from door station. Requires no extra power supply for door release. An AC operated door strike is required.
- Existing doorbell or chime wires can be utilised (disconnect from transformer).
- Master station is equipped with Door Release and one Function button to turn on entrance light, etc.
- Optional call extension sounder.

Specifications

Power Source	AC 15V, supplied from Power Supply.		
Calling	Electronic tone (while the button is depressed).		
Communication	Simultaneous with handset.		
Weight	DA-1MD: approximately 370 g. DA-1DS: approximately 270 g.		
Wiring	2 wires, polarised from door to DA-1MD.		
Distance			
Diameter	0.6 mm	0.8 mm	1.0 mm
From door to master station	110 m	200 m	310 m
Master station to Power supply	55 m	100 m	155 m

System components

- DA-1AS Kit consists of DA-1DS & DA-1MD.
- DA-1AG Kit consists of DA-1DG & DA-1MD.
- Power supply required 15 VAC 500.

Additional Options



DAR-1
Call extension
sounder.



EL-9S
Door release,
AC 16 V, 20AΩ.



Gate, Light, Garage
Door. Switch contact
is rated at 40mA
24 volt.

15 VAC 500
Power supply.



2 Wires

Your local Aiphone reseller:



COMMUNICATION SYSTEMS
AIPHONE[®]
HOME, BUSINESS, INDUSTRY.